

MERCURY 130W USER MANUAL**1. MAKING A SALE****A. Single sale transaction**

Switch on the machine by pressing and holding the **VD/MODE** button until it produces a beep sound.

From 1..... or sales mode press **TOTAL** and machine displays **0.00**, Enter the price which is **VAT INCLUSIVE**. Press the small one dot (**1.**) for **16% VAT Rate**. Then press **STL** to confirm whether amount is correct then press **TOTAL**. Machine prints a receipt.

B. Selling with PLUs

From 1..... or sales mode press **TOTAL** and machine displays **0.00**, Enter the price which is **VAT INCLUSIVE**. Press **SH** and **PLU**.

Enter the **PLU** code number then press **PLU**, Press **TOTAL** to issue the receipt.

C. Selling with quantities

Press **TOTAL** to display **0.00**

Enter the number of quantities and press **QTY** button

Enter the price which is **VAT inclusive**. Press **SH** and **PLU**.

Enter **PLU** code number then press **PLU**.

Press **TOTAL** to issue out the receipt.

2. MULTIPLE ITEMS/SERVICES

Press **TOTAL** to display 0.00

Enter the total amount **VAT INCLUSIVE**.

Press **SH** and **PLU**.

Enter **PLU** code number and press **PLU**.

Enter price of the next item and press **SH** and **PLU**.

Enter the **PLU** code and press **PLU**.

Press total to issue out receipt.

FOR SUPPORT CONTACT: 0727 341653/ 0792 874653/ 07220998360 EMAIL:

technical@carlnkyle.co.ke / info@carlnkyle.co.ke

WEBSITE: www.carlnkyle.co.ke LOCATED AT The Bazaar Plaza M1, Moi Avenue adjacent to Biashara Street.

VOIDING A SALE

To void a sale press **SH** then **00** button to fully cancel the transaction.

To cancel partially press **VD/MODE** twice.

NOTE: A sale can only be voided before pressing **TOTAL**.

3. SELLING WITH BUYERS PIN

Machine displaying 0.00 press **SH** then **PY1** to prompt you where you key in the numbers i.e.. if pin starts with **A** press **1**, and if starting with **P** press **2**. Then the machine displays **cl pin**. Here you enter the **9 digits** of the pin then press **TOTAL** and device displays **01.00**.

Enter the last letter of the PIN according to the **Asci code** table below and then press **TOTAL**. Machine prints out the pin, press **STL**, to confirm then press **TOTAL** to return to sales mode then make the sale to get a receipt with the buyers pin.

ASCII CODES

A—065 B--066 C—067 D—068 E—069
 F—070 G--071 H—072 I--073 J—074
 K--075 L—076 M--077 N--078 O—079
 P--080 Q--081 R—082 S--083 T—084
 U--085 V--086 W--087 X—088 Y—089
 Z—090

E.G. I want to input the **pin: P051836405I**, after I've pressed **SH** then **PY1**, I will select option **2** because the pin starts with **P** then I will enter the **nine digits** as **051836405** then press **TOTAL** and machine displays **01.000**, from here I have to key in **073** for the letter **I** and **TOTAL** button and the machine prints the pin and then press **STL** key to confirm the pin is correct, press **TOTAL OR STL** to go back

FOR SUPPORT CONTACT: 0727 341653/ 0792 874653/ 07220998360 EMAIL:
technical@carlnkyle.co.ke / info@carlnkyle.co.ke
WEBSITE: www.carlnkyle.co.ke LOCATED AT The Bazaar Plaza M1, Moi Avenue
adjacent to Biashara Street.

to **0.00** where I will continue with the sale normally and the receipt will have the buyers pin.

MAKING/ISSUING A CREDIT

While at **0.00**, Press **Minus (-)**, it will indicate **rcp n** Enter the receipt number e.g. **20**.

Press **Total**, it will indicate (- **0.00**)

Sell as you had sold in the receipt you are generating a credit for.

Receipt number is the CU INVOICE NUMBER as indicated in each receipt. You only have to use the last digits. Ie. For CU INVOICE NUMBER: 00400021300000000020 you will only use 20.

MAKING A DEBIT

While at **0.00**, Press **Plus (+)**, it will indicate **rcp n** Enter the receipt number e.g. **20**.

Press **Total**, it will indicate (d **0.00**)

Sell as you had sold in the receipt you are generating a credit for.

MAKING A COPY

When at **0.00** press **decimal point** and enter the receipt number (**CU INVOICE NUMBER**) then press **SH** then **QTY** and you'll get a copy of that receipt.

Receipt number is the CU INVOICE NUMBER. You only have to use the last digits. For CU INVOICE NUMBER: 004000213000000000146 you will use 146.

CONNECTING TIMS MACHINE TO WIFI NETWORK

a. CONNECTING TO MOBILE/PHONE HOTSPOT •

- Go to mobile Hotspot setting and note down the Wi-Fi name and password (you can change the name to a simple name Wi-Fi name and Password:
- Go to TIMS machine (Mercury 181/130W/133) Power on and go to mode 1/Registration mode.
- Press **STL** button and Wait for the device to show F, Started/WIFI SETUP.
- Go to mobile phone or Laptop. Go to Wi-Fi list and connect to Wi-Fi broadcasted as

FOR SUPPORT CONTACT: 0727 341653/ 0792 874653/ 07220998360 EMAIL: technical@carlnkyle.co.ke / info@carlnkyle.co.ke

WEBSITE: www.carlnkyle.co.ke LOCATED AT The Bazaar Plaza M1, Moi Avenue adjacent to Biashara Street.

(KRAMW0090----)

- Go to your browser e.g., Chrome, Mozilla, or Firefox and Enter default IP address 192.168.1.1 on your Browser and search.
 - Opens a tab with **Incotex Control Unit Communication settings**, Click **Log in**.

- Enable Wi-Fi connection parameters.
- Key in the SSID (WIFI name) and the password for the Wi-Fi noted down in the first step.
- Submit WIFI and log out then Go to your Hotspot setting and turn on Hotspot and turn on mobile data.
- Go back to your TIMS device and Press the **(C)** button on the machine.
- Press 1 then **STL** Button to make a connection test.
- When you get **connection test: Fault!** Recheck you Wi-Fi name and password.
- When you get **connection test: ok** (well done WiFi set up successfully done).
- Press QTY to print a status report.

b. CONNECTING TO WIFI FROM ROUTER

- Get the Wi-Fi name and Password and note it down.
- Go to TIMS machine (Mercury 181/130W/133) and Power it on, go to mode 1/Registration mode
- Press STL button and Wait for the device to display **F, Started/WIFI SETUP**.
- Go to your mobile phone or Laptop.
- Go to Wi-Fi list and connect to Wi-Fi broadcasted as (KRAMW00900.....)
- Go to your browser e.g., Chrome, Mozilla, or Firefox.
- Enter default IP address 192.168.1.1 on your Browser and search,
- It Opens a tab with **Incotex Control Unit Communication settings**, Click **Log in**.
- Enable Wi-Fi connection parameters
- Key in the SSID (WIFI name) and the password for the Wi-Fi noted down in the first step.
- Submit WIFI and log out.
- Go back to your TIMS device and Press **{C}** button on the machine.
- Press 1 then **STL** Button to make a connection test.
- If you get connection test: Fault! Recheck your WiFi name and password repeat the setup process.
- If you get connection test: ok (well-done Wi-Fi set up successfully done).
- Press QTY to print a status report.

FOR SUPPORT CONTACT: 0727 341653/ 0792 874653/ 07220998360 EMAIL:

technical@carlnkyle.co.ke / info@carlnkyle.co.ke

WEBSITE: www.carlnkyle.co.ke LOCATED AT The Bazaar Plaza M1, Moi Avenue adjacent to Biashara Street.

MAKING MONTHLY REPORTS SUMMARY REPORT

- Go to **X REPORT MODE**, Press total
- Key in **1** then **STL** (Machine will request for the beginning date key in the beginning date in format (DDMMYY) e.g.,010122 then press **QTY** it will request for the END DATE
- Key in the end date (DDMMYY) e.g., 310122 then press **VD/MODE** to issue the periodic report.
- For a DETAILED REPORT, go to Z REPORT then press total. Key in 4 then **STL** (Machine will request for the beginning date for the period. Key in the beginning date in format (DDMMYY) e.g.,010122 • Press **QTY** then Key in the end date (DDMMYY) e.g., 310122 • Press **VD/MODE** to issue the periodic report.

Carl & Kyle Solutions

FOR SUPPORT CONTACT: 0727 341653/ 0792 874653/ 07220998360 EMAIL:
technical@carlnkyle.co.ke/info@carlnkyle.co.ke
WEBSITE: www.carlnkyle.co.ke LOCATED AT The Bazaar Plaza M1, Moi Avenue
adjacent to Biashara Street.

